

Secuyou Smart Lock

User manual - MATTER version 1.0

March 2024

Pair the lock with MATTER

March 2024

Add lock

Step 1

- Press and hold the UNLOCK button for more than three seconds

GREEN LED flashes fast (2-3 times per second) and the RED LED flashes slow (1 time per second)

Bluetooth LE advertising is enabled for 15 minutes and makes the Secuyou Smart Lock discoverable for a Thread border router

The Secuyou Smart Lock is in the unprovisioned (unpaired) state and is waiting to be commissioned through a Thread-Border-Router



March 2024

Add lock

Step 2 (for iOS users)

- Go to the HOME app on your iOS device
 1. Open the Home app and tap Add
 2. Tap Add Accessory
 3. Use the camera on your iPhone or iPad to scan the QR code on the box of the accessory (Secuyou Smart Lock). If you have an iPhone 7 or later and see on your accessory, hold your iPhone near the accessory to add it

When the GREEN LED flashes rapidly (4 times per second), the Secuyou Lock is in the unprovisioned state and a commissioning process is started over Bluetooth LE

4. When your accessory appears, tap it. If asked to Add Accessory to Network, tap Allow

During commissioning the LED's turn off

5. Assign a passcode and add your accessory to a room and name it to help you identify it in the Home app and control it with Siri

March 2024

Reference: <https://support.apple.com/en-us/HT204893>

How does the Secuyou Smart Lock work?

March 2024

How does it work?

Add automation on iOS Home app or Google Home app

- The Secuyou Smart Lock can be locked and unlocked from the iOS Home app or Google Home app
- The Secuyou Smart Lock can be locked and unlocked by use of the UNLOCK button
- When initiating a locking action the RED LED will flash rapidly. When locking is completed the RED LED will stay solid on for one second
- When initiating an unlocking action the GREEN LED will flash rapidly. When locking is completed the GREN LED will stay solid on for one second



March 2024

How does it work?

Add automation on iOS Home app or Google Home app

- The Secuyou Smart Lock can be locked and unlocked from the iOS Home app, Google Home app by using scenes (e.g. coming home) or through voice control
- The Secuyou Smart Lock can always be locked and unlocked by use of the UNLOCK button in Homelock mode



Homelock

Homelock is when UNLOCK button is always active

- In Homelock mode you can always lock and unlock by use of the UNLOCK button. By default Homelock is on (active)
- To deactivate Homelock you need to set the lock in privacy mode (Operating Mode)
- When Homelock is deactivated (lock is in Privacy mode) you cannot unlock the lock by use of the UNLOCK button
- To activate Homelock you need to set the lock in Normal mode



March 2024

What does the LED tell me (1/2)?

Locking

- When initiating a locking action the RED LED will flash rapidly. When locking is completed the RED LED will stay solid on for one second

Unlocking

- When initiating an unlocking action the GREEN LED will flash rapidly. When locking is completed the GREEN LED will stay solid on for one second



What does the LED tell me (2/2)?

Locking is blocked

- If the lock is blocked from locking the RED LED will flash fast (4 times per second) for about 5 seconds

Unlocking is blocked

- If the lock is blocked from unlocking the GREEN LED will flash fast (4 times per second) for about 5 seconds



Factory reset

March 2024

Factory reset

- Press and hold the PRG button
- First the GREEN LED starts flashing - now factory reset is initiated (important to keep pressing the button)
- After approximately 10 seconds the GREEN LED will start flashing (1 time per second) and the RED LED will stay solid on - now the lock is factory reset
- In factory reset mode the Secuyou Smart Lock MATTER can locked and unlocked by pressing the UNLOCK button
- The LED's will turn off when the lock is locked and unlocked in factory reset mode
- Pull out the batteries and insert again and the LED's will indicate if the lock is in factory reset mode (GREEN LED flashes and the RED LED is solid on)



March 2024